


**MonoRail Surface Transformer-300W EI**



**DESCRIPTION**

This single-feed surface transformer converts standard 120 line-voltage to 12 volts to provide the necessary voltage for powering a MonoRail low-voltage lighting system. It can power lamps totaling up to 300 watts. The transformer is concealed inside a decorative housing with a single integral power feed and fast acting secondary short circuit and overload protection that will safely turn the system off should a short occur. Once the short has been removed, the unit can be reset by simply flipping the wall switch off and on.

**INSTALLATION**

This product can mount to either 4" square electrical box with round plaster ring or an octagon electrical box (not included). Rail is installed through the power feed on the canopy to bring power to the run. The power connector can be mounted on top of the canopy or to its side.

**DIMMING**

Dimmable with a 600 watt low-voltage electronic dimmer. The dimmer is placed on the line side of the transformer. (Consult dimmer manufacturer for specifics).

**OTHER INFORMATION**

Black and white finish have satin nickel feeds. The shortest rigid standoff that can be used with this surface transformer is the 4" rigid standoff (sold separately). If dropping the rail more than 4" below the ceiling, order the desired rigid standoff length and one compatible power extender (sold separately). This surface transformer may be plugged in with the addition of a Plug Option, a 16' cord with plug (sold separately). 12 volt transformers require the use of 12 volt lamps.

**WEIGHT**

3.4lb / 1.54kg

**ORDERING INFORMATION**

**700MOSRT30E FINISH**

- Z ANTIQUE BRONZE
- B BLACK
- C CHROME
- S SATIN NICKEL
- W WHITE



7400 Linder Avenue T 847.410.4400  
 Skokie, Illinois 60077 F 847.410.4500

[www.techlighting.com](http://www.techlighting.com)

700MOSRT30E \_\_\_\_\_

FIXTURE TYPE: \_\_\_\_\_

JOB NAME: \_\_\_\_\_

NOTES: \_\_\_\_\_  
 \_\_\_\_\_  
 \_\_\_\_\_

