

NON-ENCLOSED ELECTRONIC

Transformers

WAC LIGHTING

Responsible Lighting®



Fixture Type:

Catalog Number:

Project:

Location:

PRODUCT DESCRIPTION

Low Voltage electronic transformer designed to be used as a replacement part for factory installed transformers or installed in a properly listed enclosure.

FEATURES

- 1W minimum load
- All connections must be made in an enclosure for proper installations
- Dimmable with electronic low voltage dimmers. Dimmers should always be installed on the primary side of the transformer.

SPECIFICATIONS

Construction: Built-in auto reset, soft start, short and overload circuit protection features. The soft start delayed start feature extends lamp life by delaying the abrupt inrush current to the lamp.

Output: 12V

Frequency: 20khz

Details: In the case of a system overload or short circuit the transformer will revert to a "hold" position and then automatically reset the system when the problem is solved. System protection is designed to last several hours.

Standards: UL recognized component part.

ORDER NUMBER

Model	Output	L	W	H
EN-1260-R-AR	12V, 60W	2½"	1¾"	1"
EN-1275-R-AR	12V, 75W	2½"	1¾"	1"
EN-1260-R2*	12V, 60W	2½"	1¾"	1"
EN-1260N-R2*	12V, 60W	2½"	1¾"	1"

*U.L. Listed Class 2 Component

ACCESSORIES

Model		L	W	H
MTB-01	Multiple Terminal Block	3¼"	1¾"	7/8"
METB	Enclosure & Connection Box	6½"	1½"	1½"

EN - - **R-AR**

Example: **EN-24150-R-AR**

WAC Lighting

www.waclighting.com

Phone (800) 526.2588 • Fax (800) 526.2585

Headquarters/Eastern Distribution Center

44 Harbor Park Drive • Port Washington, NY 11050

Phone (516) 515.5000 • Fax (516) 515.5050

Western Distribution Center

1750 Archibald Avenue • Ontario, CA 91760

Phone (800) 526.2588 • Fax (800) 526.2585