MonoRail Surface Transformer-300W Mag







DESCRIPTION

This single-feed surface transformer converts standard 120 line voltage to 12 volts to provide the necessary voltage for powering a MonoRail low-voltage lighting system. It can power lamps totaling up to 300 watts. The transformer is concealed inside a decorative housing with a fast acting secondary circuit breaker that will safely turn the system off should a short occur. Once the short has been removed the breaker can be reset.

INSTALLATION

This product can mount to either a 4" square electrical box with round plaster ring or an octagon electrical box (not included). Rail is installed through the power feed on the canopy to bring power to the run.

DIMMING

Dimmable with a 600 watt low-voltage magnetic dimmer. The dimmer is placed on the line side of the transformer. (Consult dimmer manufacturer for specifics). This surface transformer includes a preinstalled debuzzing dimming coil to reduce audible noise when using a low-voltage dimmer.

OTHER INFORMATION

Black and white finish have satin nickel feeds. The shortest rigid standoff that can be used with this surface transformer is the 4" rigid standoff (sold separately). If dropping the rail more than 4" below the ceiling, order the desired rigid standoff length and one compatible power extender (sold separately). This surface transformer may be plugged in with the addition of a Plug Option, a 16' cord with plug (sold separately). 12 volt transformers require the use of 12 volt lamps.

WEIGHT

12.15lb / 5.51kg

ORDERING INFORMATION

700MOSRT30D FINISH

- Z ANTIQUE BRONZE
- **B** BLACK
- C CHROME
- S SATIN NICKEL
- \mathbf{w} white



7400 Linder Avenue Skokie. Illinois 60077 T 847.410.4400 F 847.410.4500

www.techlighting.com

700MOSRT30D	
FIXTURE TYPE: JOB NAME: NOTES:	

