CATALOG NUMBER TYPE 615 South Street Garden City, NY 11530 Tel:516-515-5000 Fax:516-515-5050 www.waclighting.com 🖌 WAC LIGHTING PROJECT Responsible Lighting LOW VOLTAGE ELECTRONIC TRANSFORMER MODEL EN-1260-RB2-T 6 1/2" -1 2/3" 4'' 11 **Ordering Matrix** Model Finish Accessories

ModelFinishAccessoriesEN-1260-RB2-TBKSee table below

Ordering Example (model-finish): EN-1260-RB2-T

## **Product Details**

Product Details		Sp	ecification Features
Description:	Low Voltage Class II electronic transformer designed to be used as an enclosed remote transformer. Enclosure has separate compartments for transformer, line and low voltage wiring. Be recommended to use for LED tapelight and halogen lamp.	•	U.L. 2108 listed Class II electronic low voltage transformer.
Catalog Number:	EN = Advanced electronic circuitry 1260 = 12 volt , 60 watt RB = Remote Boxed, Class II AR = Auto-Reset T = Be used for Tapelight only	•	Built-in auto reset, soft start, short and overload circuit protection features. The soft start delayed start feature extends lamp life by delaying the
Input:	120V (50/60Hz)		abrupt inrush current to the lamp.
Output:	12V		
Min Load:	10W	•	Class II transformers are inherently protected and power
Max Load:	60W		limited, protecting the lighting
Max Input Amp:	0.53A (@ 120V)		system from both normal and abnormal short circuits
Transformer	20khz.		
Frequency:	True RMS meter is required to read the high frequency output.	•	Enclosure has knockouts on three sides. Screw holes are
Dimming:	Be dimmable while it is used for halogen lamp as other electronic transformers (e.g: EN-1260-RB2); For LED tapelight only, it's no dimming.		located on one long side for securing enclosure in place.
Listing:	U.L. listed, File Number E204239.		Events WAC Lighting product
Accessories:	MTB-01 – Multiple Terminal Block	•	5 years W.A.C. Lighting product warranty.

W.A.C. Lighting reserves the right to modify the design of our products as part of the company's continuous improvement program.

Specification Features