

SMALL



15231 AZT, BKT

MEDIUM



15241 AZT, BKT

| | | |
|---------------------------|--|--|
| Ordering Guide & Finish | 15231 AZT, BKT | 15241 AZT, BKT |
| Housing | Cast Aluminum. Tempered convex glass lens. | Cast Aluminum. Tempered convex glass lens. |
| Lamp Base | 4000V (4KV) pulse rated medium base porcelain socket | 4000V (4KV) pulse rated medium base porcelain socket |
| Supplied Lamp | Lamp not supplied unless noted | Lamp not supplied unless noted |
| Incandescent Lamp Options | 35-W Max. PAR20 Metal Halide or 50-W Max. PAR20/R20 Incandescent | 70-W Max. PAR30L Metal Halide or 75-W(VA) PAR30L/R30 Incandescent |
| LED Lamp Options | 7W PAR20 Wet (18081-18086) see page 166. Compares up to 35W Halogen. | 12W PAR30L Wet (18111-18116) see page 166. Compares up to 50W Halogen. |
| Wiring | 8" of usable 200°C 18 AWG wire leads. | 8" of usable 200°C 18 AWG wire leads |
| Optional Mounting Access. | 15276 – Power Post® 15601 – Surface Mounting Flange, for attachment to junction box (not included) 15609 – Junction Box Mounting Bracket | 15276 – Power Post® 15601 – Surface Mounting Flange, for attachment to junction box (not included) 15609 – Junction Box Mounting Bracket |
| Optional Lens Accessories | 15620 – Medium Cowl 15628 – Long Cowl 15623 – Blue Filter 15637 – Hexcell Louver | 15640 – Medium Cowl 15648 – Long Cowl 15624 – Blue Filter 15638 – Hexcell Louver |
| Notes | Accents require remote ballasts for High Intensity Discharge. See HID Ballast Guide on page 159 and 120V Lamp Guide on page 166. For Lamp Photometrics see page 169. | Accents require remote ballasts for High Intensity Discharge. See HID Ballast Guide on page 159 and 120V Lamp Guide on page 166. For Lamp Photometrics see page 169. |