

## Lighting Your Life Since 1970

Product Specifications - 87851MB		
Job Name:	Job Type:	
Quantity:	Comments	



## 87851MB

CounterMax MX-X12 13" 2-LT 12V Xenon Starter Kit

Finish	Glass/Shade	Product Category
Metallic Bronze		Under Cabinet Kit

Lamping Number of Bulbs	2	Measuren Width
Light Type	Xenon	Height
Bulb Type	12V Wedge T5 Xelogen	Length
Max Bulb Wattage	18	Extension
Max Fixture Wattage	36	Back Plat
Rated Life	±10,000 Hours	<b>Back Plat</b>
Rated Lumens	±528	HCO
Color Temp	±2,900 K	Min Overa
Bulb(s)	Included	Max Over
Light Up/Down	N/A	Hanging \
Beam Spread	N/A	Height Ac
CRI	N/A	Slope
Photo Cell Included	N/A	Chain Ler
Ballast/Driver/Transformer	Yes	Wire Leng
Dimmable	Low-Voltage	Canopy V

Measurements	
Width	5.0"
Height	1.1"
Length	13.0"
Extension	N/A
Back Plate Width	N/A
Back Plate Height	N/A
HCO	N/A
Min Overall Height	N/A
Max Overall Height	N/A
Hanging Weight	1.7 lbs
Height Adjustable	N/A
Slope	N/A
Chain Length	N/A
Wire Length	N/A
Canopy Width	N/A
Canopy Height	N/A
Canopy Length	N/A

	Shipping	
"	Carton Weight	1.7 lbs
"	Carton Width	4"
"	Carton Height	3"
١	Carton Length	18"
١	Carton Cubic Feet	0.14
١	Master Pack	6
١	Master Pack Weight	12.8 lbs
١	Master Pack Width	13.0"
١	Master Pack Height	7.1"
3	Master Pack Length	18.1"
١	Master Cubic Feet	0.97
١	UPS Shippable	Yes
١		

Certification		Other		Equivalents	
Safety Rating	Dry	UPC Code	783209064249	Incandescent Watts	N/A
Energy Star	No	Shades Included	N/A	Fluorescent Watts	N/A
CA Title 24	No	Crystals Included	N/A		
CA Title 20	No	Diffuser Included	N/A		
ADA	No	Conversion Kit	N/A		
Dark Sky	N/A	Material	Steel		

Maxim Lighting International and all designs, logos and images © 2013 Maxim Lighting International. All Rights Reserved. Maxim Lighting International reserves the right, at any time, to make changes in the design and/or construction of the product including the discontinuation of product without prior notice. Color may vary from what is pictured above due to limitations inherent to photographic processes.

Always consult a qualified, licensed electrician before installation of any product weighing 35 pounds or more. We recommend that a qualified, licensed electrician do the installation. Always install to a mechanically sound structure.