

## Lighting Your Life Since 1970

Product Specifications - 87843MB			
Job Name:	Job Type:		
Quantity:	Comments		



## 97942ME

CounterMax MX-X120c 30" 4-Light 120V Xenon

N/A N/A

N/A

N/A

Finish Metallic Bronze		Glass/Snade		Under Cabinet	
Lamping		Measurements		Shipping	
Number of Bulbs	4	Width	5.0"	Carton Weight	
Light Type	Xenon	Height	1.3"	Carton Width	
Bulb Type	G8	Length	30.0"	Carton Height	

**Canopy Length** 

Number of Bulbs	4	Width
Light Type	Xenon	Height
Bulb Type	G8	Length
Max Bulb Wattage	20	Extension
Max Fixture Wattage	80	Back Plate Width
Rated Life	±3,500 Hours	Back Plate Height
Rated Lumens	±900	НСО
Color Temp	±2,900 K	Min Overall Height
Bulb(s)	Included	Max Overall Height
Light Up/Down	N/A	Hanging Weight
Beam Spread	N/A	Height Adjustable
CRI	N/A	Slope
Photo Cell Included	N/A	Chain Length
Ballast/Driver/Transformer	No	Wire Length
Dimmable	Standard	Canopy Width
		Canopy Height

	Shipping	
5.0"	Carton Weight	3.3 lbs
1.3"	Carton Width	7'
30.0"	Carton Height	3'
N/A	Carton Length	34'
N/A	Carton Cubic Feet	0.32
N/A	Master Pack	6
N/A	Master Pack Weight	21.5 lbs
N/A	Master Pack Width	13.9'
N/A	Master Pack Height	9.0'
3.3 lbs	Master Pack Length	34.9'
N/A	Master Cubic Feet	2.52
N/A	UPS Shippable	Yes
N/A		

Certification		Other		Equivalents	
Safety Rating	Dry	UPC Code	783209073371	Incandescent Watts	N/A
Energy Star	No	Shades Included	N/A	Fluorescent Watts	N/A
CA Title 24	No	Crystals Included	N/A		
CA Title 20	No	Diffuser Included	N/A		
ADA	No	Conversion Kit	N/A		
Dark Sky	N/A	Material	Steel		

Maxim Lighting International and all designs, logos and images © 2013 Maxim Lighting International. All Rights Reserved. Maxim Lighting International reserves the right, at any time, to make changes in the design and/or construction of the product including the discontinuation of product without prior notice. Color may vary from what is pictured above due to limitations inherent to photographic processes.

Always consult a qualified, licensed electrician before installation of any product weighing 35 pounds or more. We recommend that a qualified, licensed electrician do the installation. Always install to a mechanically sound structure.