


615 South Street Garden City, NY 11530 Tel:516-515-5000 Fax:516-515-5050 www.waclighting.com


	CATALOG NUMBER
•	PROJECT

TYPE

3" LOW VOLTAGE MINIATURE HOUSING

HR-802





Ordering Matrix		_
Series	Model Number	Trim
HR	802	See page two

Ordering Example (series - model number + trim): HR-802

Product Deta	ils	_Sp	ecification Features
Description:	Low voltage new construction downlight with integral electronic transformer for ceilings, soffits, and other low profile applications.	•	Small sized new construction housing is compact enough to fit
Materials:	Housing and junction box are 20 gauge steel, painted black. Frame and hanger bars are heavy gauge galvanized steel. Electrical component within can is a bi-pin ceramic socket with 18 gauge teflon insulated wires with fiberglass sleeves.		in 2x6 joist installations, allowing these to be used in "shallow" applications.
Transformer:	Electronic transformer for 12 volt MR16 lamps, 50w maximum. 120V input transformer.	•	Electronic transformer has advanced auto-reset, soft start and short circuit protection
J-Box:	Three ½" knockouts provided for wire entry and exit. Suitable for chain wiring.		features. Handles mounting surface
Mounting:	Supplied with hanger bars, adjustable from 12"-24" to accommodate		thickness up to $\frac{3}{4}$ ".
	various joist construction and grid sizes. Hanger bars have slots for easy mounting on "T" bars. 3" cutout hole.	•	Dims with electronic low voltage dimmers.
Ratings:	Non-IC rated. Insulation must be kept at least 3" away from housing. UL and CUL listed. Suitable for damp locations. Thermal protector protects against over-lamping.	•	5 year WAC Lighting product warranty.



615 South Street Garden City, NY 11530 Tel:516-515-5000 Fax:516-515-5050 www.wadighting.com

|--|

PROJECT

<u>TYPE</u>

HR-802

3" LOW VOLTAGE MINIATURE HOUSING

Compatible Trims (sold separately): HR-833-HR-834-HR-836-Finishes: BN, WT Finishes: BN, CB, WT, Finishes: BK, BN, CB, PB, WT/WT WΤ Lamp: MR16 35W max. Lamp: MR16 35W max. Lamp: MR16 35W max. HR-837-Finishes: BK, BN, CB, CH, PB, WT Lamp: MR16 35W max.

Finish Key:

BK-Black, BN-Brushed Nickel, CB-Copper Bronze, CH-Chrome, PB-Polished Brass, WT-White

Notes: The full catalog number for a complete downlight includes the model numbers for both the trim and the housing.

More information regarding each individual trim can be viewed on the individual trim spec sheets.

WAC Lighting reserves the right to modify the design of our products as part of the company's continuous improvement program.

Sep 2010