

Model: SRT-300M-12V

Magnetic Transformers

WAC LIGHTING

Responsible Lighting®



Fixture Type:

Catalog Number:

Project: _____

Location: _____

PRODUCT DESCRIPTION

Long lasting and reliable Magnetic Transformers offer multiple secondary output terminals to compensate for voltage drop, auto reset overload and short circuit protection while complying with the highest level of safety and performance standards.

FEATURES

- Larger and generally have greater capacities than electronic models
- Allow for greater wiring distances from transformer to the powered equipment
- Multi-taps from 12V up to 15V or from 24V up to 30V, compensate for voltage drop
- Feature "push-to-reset" circuit breakers
- Complies with UL2108 standards for low voltage installations

SPECIFICATIONS

Input: 120V (50/60Hz)

Output: 12V

Frequency: 20khz

Standards: UL & CUL Listed

ORDER NUMBER

Model	Output	L	W	H
SRT-300M-12V	12V, 300W	10¾"	4¼"	4⅛"

SRT - **300M** - **12V**

Example: **SRT-300M-12V**

WAC Lighting
www.waclighting.com
Phone (800) 526.2588 • Fax (800) 526.2585

Headquarters/Eastern Distribution Center
44 Harbor Park Drive • Port Washington, NY 11050
Phone (516) 515.5000 • Fax (516) 515.5050

Western Distribution Center
1750 Archibald Avenue • Ontario, CA 91760
Phone (800) 526.2588 • Fax (800) 526.2585