



Job Name:

Contact:

Fixture Type:

Part Number:

96" ENZIS KIT



Description:

The 96" Enzis Kit utilizes Bruck's light weight Enzis track system. Available in bronze and matte chrome. Two malleable aluminum rods in the flexible track hold the desired shape even when used with suspended cable supports. It is easily field bendable to achieve any radius or hard angle, eliminating the need for angle connectors or predetermined radius measurements.

It is attached using 3 supports and transformer with power feed. Fixtures are directionally adjustable and its location can be set as desired.

Part Numbers:

340096bz

bronze, 5 Pira Spot fixtures

340096mc

matte chrome, 5 Pira Spot fixtures

340098bz

bronze, 5 Tikus fixtures

340098mc

matte chrome, 5 Tikus fixtures

Technical Specs:

300VA transformer

120V AC, 50/60Hz input

11.7V AC output

250VA, 248W for 5 (maximum 50 Watt lamp)

Suitable for dry locations only

Mount to 3" - 4" round J-box

Short circuit protection

Overload protection

Thermal protection

Dimmable

Not compatible with LED fixtures

Included:

Enzis 300W surface mount electronic transformer

Enzis end caps 2 pcs

Enzis 96" track

Enzis ceiling support 3 pcs

Enzis Pira Spot fixture 5 pcs/ or

Enzis Tikus fixture 5 pcs

50W MR16 36° lamps 5 pcs

Note:

Minimal assembly is required

