

Integral Electronic Ballast

T5 FLUORESCENT



| Lamps x Watts / Finish | WT | SS | BK |
|------------------------|--------|----------|-----------|
| 1 x 8w + 1x13w | CAF-34 | CAF-34SS | CAF-34 BK |

34" (34½"L x 5"W x 1½"H)

Integral Electronic Ballast
T5 lamp included

Lamp LF5-8 8W T5 Fluorescent, 3,000°K
 LF5-13 13W T5 Fluorescent, 3,000°K
 Finishes WT-White, SS-Stainless Steel, BK-Black
 Options General Convenience Outlet GCO-BK (Black), GCO-WT (White)

COUNTER ATTACK[®] FEATURES

Improved CounterAttack

Removable hinged diffuser; easy and safe lamp replacement

- 120V Xenon with SpeedLink™
- Three power options – Hardwire through knockouts, Interconnected with SpeedLink™ technology or portable with cord and plug option
- Longer lamp life than others due to patented cooling system
- 120V – 20 lamps maximum per power feed (700 watts)
- Fast easy installation – complete with mounting hardware
- Repositioned cooling slots.
- Porcelain sockets used for high temperature durability
- Lamps included, no tools required for relamping
- Hi-Off-Lo switch, dimmable, energy saving
- Low profile fixture – 1½" high
- Available in white, stainless steel and bronze
- Protected by multiple US patents



MOUNTING & KNOCKOUTS

Counter Attack installs easily with two easy-to-access mounting screws (provided) in keyhole slots. Fast, easy installation with multiple knockouts on ends, back and top for through-wiring, Wiremold, flex, Romex or rigid conduit.