

**FreeJack Linear Canopy 3-port**



**DESCRIPTION**

Mounts to a standard 4" junction box with round plaster ring (provided by electrician). Electronic transformers inside a 28" by 4" housing. Three FreeJack ports; for ceiling only.

**INSTALLATION**

This product can mount to either a 4" square electrical box with round plaster ring or an octagonal electrical box (not included). For ceiling only. Transformers (included) fit in canopy.

**DIMMING**

120V IN/12V OUT dimmable with a standard incandescent dimmer (not included). 120V LED dimmable with a low-voltage electronic dimmer.


**OTHER INFORMATION**

"For use with any three 12 volt halogen or LED FreeJack pendants or heads (sold separately)."

**WEIGHT**

7.3lb / 3.31kg

**ORDERING INFORMATION**



700FJL3 FINISH	VOLTAGE
Z ANTIQUE BRONZE	120V IN/12V OUT
B BLACK	
C CHROME	-277 277V IN/12V OUT
S SATIN NICKEL	
W WHITE	



**TECH LIGHTING®**

7400 Linder Avenue T 847.410.4400  
 Skokie, Illinois 60077 F 847.410.4500

[www.techlighting.com](http://www.techlighting.com)

700FJL3 \_\_\_\_\_

FIXTURE TYPE: \_\_\_\_\_

JOB NAME: \_\_\_\_\_

NOTES: \_\_\_\_\_

\_\_\_\_\_

\_\_\_\_\_

